


13.56MHz short-range Contactless memory chip with 512 bit EEPROM, Anti-Collision functions

Target Specification

Feature summary

- ISO 14443 - 2 Type B Air Interface Compliant
- ISO 14443 - 3 Type B Frame Format Compliant
- 13.56MHz Carrier Frequency
- 847kHz Sub-carrier Frequency
- 106 kbit/second Data Transfer
- 8 bit Chip_ID based anticollision system
- 2 Count-Down Binary Counters with automated anti-tearing protection
- 64-bit Unique Identifier
- 512-bit EEPROM with Write Protect Feature
- READ BLOCK and WRITE BLOCK (32 Bits)
- Internal Tuning Capacitor
- 1million ERASE/WRITE Cycles
- 40-Year Data Retention
- Self-Timed Programming Cycle
- 5ms Typical Programming Time



Contents

- 1 Summary description 7**
- 2 Signal description 8**
 - 2.1 AC1, AC0 8
- 3 Data transfer 9**
 - 3.1 Input Data Transfer from the Reader to the SRI512 (Request Frame) 9
 - 3.1.1 Character Transmission Format for Request Frame 9
 - 3.1.2 Request Start Of Frame 10
 - 3.1.3 Request End Of Frame 10
 - 3.2 Output Data Transfer from the SRI512 to the Reader (Answer Frame) .. 11
 - 3.2.1 Character Transmission Format for Answer Frame 11
 - 3.2.2 Answer Start Of Frame 11
 - 3.2.3 Answer End Of Frame 12
 - 3.3 Transmission Frame 12
 - 3.4 CRC 13
- 4 Memory mapping 14**
 - 4.1 Resettable OTP Area 15
 - 4.2 32-bit Binary Counters 16
 - 4.3 EEPROM Area 18
 - 4.4 System Area 19
 - 4.4.1 OTP_Lock_Reg 19
 - 4.4.2 OTP_Config_Bit 20
 - 4.4.3 Fixed Chip_ID (Option) 20
- 5 SRI512 operation 21**
- 6 SRI512 states 22**
 - 6.1 POWER-OFF State 22
 - 6.2 READY State 22
 - 6.3 INVENTORY State 22
 - 6.4 SELECTED State 22

6.5	DESELECTED State	22
6.6	DEACTIVATED State	23
7	Anti-collision	24
7.1	Description of an Anti-Collision Sequence	26
8	SRI512 commands	28
8.1	INITIATE() Command	29
8.2	PCALL16() Command	30
8.3	SLOT_MARKER(SN) Command	31
8.4	SELECT(Chip_ID) Command	32
8.5	COMPLETION() Command	33
8.6	RESET_TO_INVENTORY() Command	34
8.7	READ_BLOCK(Addr) Command	35
8.8	WRITE_BLOCK (Addr, Data) Command	36
8.9	GET_UID() Command	37
8.10	Power-On State	38
9	Maximum rating	39
10	DC and AC parameters	40
11	Package mechanical	42
12	Part numbering	45
Appendix A ISO14443 type B CRC calculation		46
Appendix B SRI512 command brief		47
13	Revision history	49

List of tables

Table 1.	Signal Names	7
Table 2.	Bit Description	10
Table 3.	SRI512 memory mapping	14
Table 4.	Standard Anti-Collision Sequence	26
Table 5.	Command Code	28
Table 6.	Absolute Maximum Ratings	39
Table 7.	Operating Conditions	40
Table 8.	DC Characteristics	40
Table 9.	AC Characteristics	40
Table 10.	A3 Antenna Specification	42
Table 11.	A4 Antenna Specification	43
Table 12.	A5 Antenna Specification	44
Table 13.	Ordering Information Scheme	45
Table 14.	Document revision history	49

DRAFT

List of figures

Figure 1.	Logic Diagram	7
Figure 2.	Die Floor Plan	8
Figure 3.	10% ASK Modulation of the Received Wave	9
Figure 4.	SRI512 Request Frame Character Format	9
Figure 5.	Request Start Of Frame	10
Figure 6.	Request End Of Frame	10
Figure 7.	Wave Transmitted using BPSK Sub-carrier Modulation	11
Figure 8.	Answer Start Of Frame	11
Figure 9.	Answer End Of Frame	12
Figure 10.	Example of a Complete Transmission Frame	12
Figure 11.	CRC Transmission Rules	13
Figure 12.	Resettable OTP Area (addresses 0 to 4) when OTP_Config bit = 0	15
Figure 13.	WRITE_BLOCK Update in Standard Mode (Binary Format)	15
Figure 14.	WRITE_BLOCK Update in Reload Mode (Binary Format)	16
Figure 15.	Resettable OTP Area (addresses 0 to 4) when OTP_Config bit = 1	16
Figure 16.	Binary Counter (addresses 5 to 6)	17
Figure 17.	Count Down Example (Binary Format)	17
Figure 18.	EEPROM (Addresses 7 to 15)	18
Figure 19.	System Area	19
Figure 20.	State Transition Diagram	23
Figure 21.	SRI512 Chip_ID Description	24
Figure 22.	Description of a Possible Anti-Collision Sequence	25
Figure 23.	Example of an Anti-Collision Sequence	27
Figure 24.	INITIATE Request Format	29
Figure 25.	INITIATE Response Format	29
Figure 26.	INITIATE Frame Exchange Between Reader and SRI512	29
Figure 27.	PCALL16 Request Format	30
Figure 28.	PCALL16 Response Format	30
Figure 29.	PCALL16 Frame Exchange Between Reader and SRI512	30
Figure 30.	SLOT_MARKER Request Format	31
Figure 31.	SLOT_MARKER Response Format	31
Figure 32.	SLOT_MARKER Frame Exchange Between Reader and SRI512	31
Figure 33.	SELECT Request Format	32
Figure 34.	SELECT Response Format	32
Figure 35.	SELECT Frame Exchange Between Reader and SRI512	32
Figure 36.	COMPLETION Request Format	33
Figure 37.	COMPLETION Response Format	33
Figure 38.	COMPLETION Frame Exchange Between Reader and SRI512	33
Figure 39.	RESET_TO_INVENTORY Request Format	34
Figure 40.	RESET_TO_INVENTORY Response Format	34
Figure 41.	RESET_TO_INVENTORY Frame Exchange Between Reader and SRI512	34
Figure 42.	READ_BLOCK Request Format	35
Figure 43.	READ_BLOCK Response Format	35
Figure 44.	READ_BLOCK Frame Exchange Between Reader and SRI512	35
Figure 45.	WRITE_BLOCK Request Format	36
Figure 46.	WRITE_BLOCK Response Format	36
Figure 47.	WRITE_BLOCK Frame Exchange Between Reader and SRI512	37
Figure 48.	GET_UID Request Format	37

Figure 49.	GET_UID Response Format.	37
Figure 50.	64-bit Unique Identifier of the SRI512.	38
Figure 51.	GET_UID Frame Exchange Between Reader and SRI512	38
Figure 52.	SRI512 Synchronous Timing, Transmit and Receive	41
Figure 53.	A3 Antenna Specification	42
Figure 54.	A4 Antenna Specification	43
Figure 55.	A5 Antenna Specification	44
Figure 56.	INITIATE Frame Exchange Between Reader and SRI512.	47
Figure 57.	PCALL16 Frame Exchange Between Reader and SRI512	47
Figure 58.	SLOT_MARKER Frame Exchange Between Reader and SRI512.	47
Figure 59.	SELECT Frame Exchange Between Reader and SRI512	47
Figure 60.	COMPLETION Frame Exchange Between Reader and SRI512	47
Figure 61.	RESET_TO_INVENTORY Frame Exchange Between Reader and SRI512	48
Figure 62.	READ_BLOCK Frame Exchange Between Reader and SRI512	48
Figure 63.	WRITE_BLOCK Frame Exchange Between Reader and SRI512	48
Figure 64.	GET_UID Frame Exchange Between Reader and SRI512	48


DRAFT

1 Summary description

The SRI512 is a contactless memory, powered by an externally transmitted radio wave. It contains a 512-bit user EEPROM fabricated with STMicroelectronics CMOS technology. The memory is organized as 16 blocks of 32 bits. The SRI512 is accessed via the 13.56MHz carrier. Incoming data are demodulated and decoded from the received Amplitude Shift Keying (ASK) modulation signal and outgoing data are generated by load variation using Bit Phase Shift Keying (BPSK) coding of a 847kHz sub-carrier. The received ASK wave is 10% modulated. The Data transfer rate between the SRI512 and the reader is 106kbit/s in both reception and emission modes.

The SRI512 follows the ISO 14443 part 2 type B recommendation for the radio-frequency power and signal interface.

Figure 1. Logic Diagram



The SRI512 is specifically designed for short range applications that need re-usable products. The SRI512 includes an anti-collision mechanism that allows it to detect and select tags present at the same time within range of the reader. Using the STMicroelectronics single chip coupler, CRX14, it is easy to design a reader and build a contactless system.

Table 1. Signal Names

AC1	Antenna Coil
AC0	Antenna Coil

The SRI512 contactless EEPROM can be randomly read and written in block mode (each block containing 32 bits). The instruction set includes the following nine commands:


- READ_BLOCK
- WRITE_BLOCK
- INITIATE
- PCALL16
- SLOT_MARKER
- SELECT
- COMPLETION
- RESET_TO_INVENTORY
- GET_UID

The SRI512 memory is organized in three areas, as described in [Table 3](#). The first area is a resettable OTP (one-time programmable) area in which bits can only be switched from 1 to 0. Using a special command, it is possible to erase all bits of this area to 1. Optionally, this area can be set as an EEPROM area where all blocks behave as User blocks. This option is set by ST on request.

The second area provides two 32-bit binary counters that can only be decremented from FFFFFFFFh to 00000000h, and gives a capacity of 4,294,967,296 units per counter.

The last area is the EEPROM memory. It is accessible by block of 32 bits and includes an auto-erase cycle during each WRITE_BLOCK command.

Figure 2. Die Floor Plan



2 Signal description

2.1 AC1, AC0


The pads for the Antenna Coil. AC1 and AC0 must be directly bonded to the antenna.

3 Data transfer

3.1 Input Data Transfer from the Reader to the SRI512 (Request Frame)

The reader must generate a 13.56MHz sinusoidal carrier frequency at its antenna, with enough energy to “remote-power” the memory. The energy received at the SRI512’s antenna is transformed into a Supply Voltage by a regulator, and into data bits by the ASK demodulator. For the SRI512 to decode correctly the information it receives, the reader must 10% amplitude-modulate the 13.56MHz wave before sending it to the SRI512. This is represented in *Figure 3*. The data transfer rate is 106 kbits/s.

Figure 3. 10% ASK Modulation of the Received Wave



3.1.1 Character Transmission Format for Request Frame

The SRI512 transmits and receives data bytes as 10-bit characters, with the least significant bit (b_0) transmitted first, as shown in *Figure 4*. Each bit duration, an ETU (Elementary Time Unit), is equal to $9.44\mu\text{s}$ ($1/106\text{kHz}$).

These characters, framed by a Start Of Frame (SOF) and an End Of Frame (EOF), are put together to form a Command Frame as shown in *Figure 10*. A frame includes an SOF, commands, addresses, data, a CRC and an EOF as defined in the ISO14443-3 type B Standard. If an error is detected during data transfer, the SRI512 does not execute the command, but it does not generate an error frame.

Figure 4. SRI512 Request Frame Character Format




Table 2. Bit Description


Bit	Description	Value
b ₀	Start bit used to synchronize the transmission	b ₀ = 0
b ₁ to b ₈	Information Byte (command, address or data)	The information byte is sent with the least significant bit first
b ₉	Stop bit used to indicate the end of a character	b ₉ = 1

3.1.2 Request Start Of Frame

The SOF described in [Figure 5](#) is composed of:

- one falling edge,
- followed by 10 ETUs at logic-0,
- followed by a single rising edge,
- followed by at least 2 ETUs (and at most 3) at logic-1.

Figure 5. Request Start Of Frame




3.1.3 Request End Of Frame

The EOF shown in [Figure 6](#) is composed of:

- one falling edge,
- followed by 10 ETUs at logic-0,
- followed by a single rising edge.


Figure 6. Request End Of Frame



3.2 Output Data Transfer from the SRI512 to the Reader (Answer Frame)

The data bits issued by the SRI512 use retro-modulation. Retro-modulation is obtained by modifying the SRI512 current consumption at the antenna (load modulation). The load modulation causes a variation at the reader antenna by inductive coupling. With appropriate detector circuitry, the reader is able to pick up information from the SRI512. To improve load-modulation detection, data is transmitted using a BPSK encoded, 847kHz sub-carrier frequency f_s as shown in *Figure 7*, and as specified in the ISO14443-2 type B Standard.

Figure 7. Wave Transmitted using BPSK Sub-carrier Modulation



3.2.1 Character Transmission Format for Answer Frame


The character format is the same as for input data transfer (*Figure 4*). The transmitted frames are made up of an SOF, data, a CRC and an EOF (*Figure 10*). As with an input data transfer, if an error occurs, the reader does not issue an error code to the SRI512, but it should be able to detect it and manage the situation. The data transfer rate is 106 kbits/second.

3.2.2 Answer Start Of Frame

The SOF described in *Figure 8* is composed of:

- followed by 10 ETUs at logic-0
- followed by 2 ETUs at logic-1

Figure 8. Answer Start Of Frame




3.2.3 Answer End Of Frame

The EOF shown in *Figure 9* is composed of:

- followed by 10 ETUs at logic-0,
- followed by 2 ETUs at logic-1.


Figure 9. Answer End Of Frame



3.3 Transmission Frame

Between the Request data transfer and the Answer data transfer, all ASK and BPSK modulations are suspended for a minimum time of $t_0 = 128/f_S$. This delay allows the reader to switch from Transmission to Reception mode. It is repeated after each frame. After t_0 , the 13.56MHz carrier frequency is modulated by the SRI512 at 847kHz for a period of $t_1 = 128/f_S$ to allow the reader to synchronize. After t_1 , the first phase transition generated by the SRI512 forms the start bit ('0') of the Answer SOF. After the falling edge of the Answer EOF, the reader waits a minimum time, t_2 , before sending a new Request Frame to the SRI512.

Figure 10. Example of a Complete Transmission Frame



4 Memory mapping

The SRI512 is organized as 16 blocks of 32 bits as shown in [Table 3](#). All blocks are accessible by the READ_BLOCK command. Depending on the write access, they can be updated by the WRITE_BLOCK command. A WRITE_BLOCK updates all the 32 bits of the block.

Table 3. SRI512 memory mapping

Block Addr	Msb b ₃₁	32 bits Block					Lsb b ₀	Description
		b ₁₆	b ₁₅	b ₁₄	b ₈	b ₇		
0		32 bits Boolean Area (option: User Area)						Resettable OTP bits (option: lockable EEPROM)
1		32 bits Boolean Area (option: User Area)						
2		32 bits Boolean Area (option: User Area)						
3		32 bits Boolean Area (option: User Area)						
4		32 bits Boolean Area (option: User Area)						
5		32 bits binary counter						Count down Counter
6		32 bits binary counter						
7		User Area						Lockable EEPROM
8		User Area						
9		User Area						
10		User Area						
11		User Area						
12		User Area						
13		User Area						
14		User Area						
15		User Area						
255		OTP_Lock_Reg	OTP_Config	ST Reserved	Fixed Chip_ID (Option)		System OTP bits	
UID0		64 bits UID Area						ROM
UID1								

4.1 Resettable OTP Area


When the OTP_Config_Bit of the system area is reset to 0, this area contains five individual 32-bit Boolean Words (see [Figure 12](#) for a map of the area). A WRITE_BLOCK command will not erase the previous contents of the block as the Write cycle is not preceded by an Auto Erase cycle. This feature can be used to reset selected bits from 1 to 0. All bits previously at 0 remain unchanged. When the 32 bits of a block are all at 0, the block is empty, and cannot be updated any more. See [Figure 13](#) and [Figure 14](#) for examples of the result of the WRITE_BLOCK command in the resettable OTP area.

Figure 12. Resettable OTP Area (addresses 0 to 4) when OTP_Config bit = 0

Block Address	MSb b31	32-bit Block b16 b15 b14	b8 b7	LSb b0	Description
0		32-bit Boolean Area			Resettable OTP Bit
1		32-bit Boolean Area			
2		32-bit Boolean Area			
3		32-bit Boolean Area			
4		32-bit Boolean Area			


ai12381

Figure 13. WRITE_BLOCK Update in Standard Mode (Binary Format)



The five 32-bit blocks making up the Resettable OTP area can be erased in one go by adding an Auto Erase cycle to the WRITE_BLOCK command. An Auto Erase cycle is added each time the SRI512 detects a Reload command. The Reload command is implemented through a specific update of the 32-bit binary counter located at block address 6 (see [Section 4.2: 32-bit Binary Counters](#) for details).

Figure 14. WRITE_BLOCK Update in Reload Mode (Binary Format)



When the OTP_Config_Bit of the system area is set to 1, the 5 blocks behave as standard EEPROM blocks. Each block can be individually write-protected using the OTP_Lock_Reg bits of the system area. Blocks 0 to 4 define a new User Area and work like blocks 7 to 15 as described in [Figure 15](#). Once a block has been protected, it can no longer be unprotected.

Figure 15. Resettable OTP Area (addresses 0 to 4) when OTP_Config bit = 1

Block Address	MSb b31	32-bit Block b16 b15 b14	b8 b7	LSb b0	Description
0		User Area			Lockable EEPROM
1		User Area			
2		User Area			
3		User Area			
4		User Area			
ai12382					

4.2 32-bit Binary Counters

The two 32-bit binary counters located at block addresses 5 and 6, respectively, are used to count down from 2^{32} (4096 million) to 0. The SRI512 uses dedicated logic that only allows the update of a counter if the new value is lower than the previous one. This feature allows the application to count down by steps of 1 or more. The initial value in the counter is FFFFFFFFh. When the value displayed is 00000000h, the counter is empty and cannot be reloaded. The counter is updated by issuing the WRITE_BLOCK command to block address 5 or 6, depending on which counter is to be updated. The WRITE_BLOCK command writes the new 32-bit value to the counter block address. [Figure 17](#) shows examples of how the counters operate.

The counter programming cycles are protected by automated anti-tearing logic. This function allows the counter value to be protected in case of power down within the programming cycle. In case of power down, the counter value is not updated and the previous value continues to be stored.

Blocks 5 and 6 can be write-protected using the OTP_Lock_Reg bits (block 255). Once a block has been protected, its contents cannot be modified. A protected counter block behaves like a ROM block.

Figure 16. Binary Counter (addresses 5 to 6)

Block Address	MSb b31	32-bit Block b16 b15 b14	b8 b7	LSb b0	Description
5	32-bit Binary Counter				Count down Counter
6	32-bit Binary Counter				

ai12384

Figure 17. Count Down Example (Binary Format)

	b31												b0			
Initial data	1	...	1	1	1	1	1	1	1	1	1	1	1	1	1	1
1-unit decrement	1	...	1	1	1	1	1	1	1	1	1	1	1	1	1	0
1-unit decrement	1	...	1	1	1	1	1	1	1	1	1	1	1	0	1	
1-unit decrement	1	...	1	1	1	1	1	1	1	1	1	1	0	0		
8-unit decrement	1	...	1	1	1	1	1	1	1	1	1	0	1	0	0	
Increment not allowed	1	...	1	1	1	1	1	1	1	1	1	1	0	0	0	

ai07661

The counter with block address 6 controls the Reload command used to reset the resettable OTP area (addresses 0 to 4). Bits b_{31} to b_{21} act as an 11-bit Reload counter; whenever one of these 11 bits is updated, the SRI512 detects the change and adds an Erase cycle to the WRITE_BLOCK command for locations 0 to 4 (see [Section 4.1: Resettable OTP Area](#)). The Erase cycle remains active until a POWER-OFF or a SELECT command is issued. The SRI512's resettable OTP area can be reloaded up to 2,047 times ($2^{11}-1$).

The Reload mechanism is active only when the OTP_Config_Bit of the system area is reset to 0. When the OTP_Config_Bit is set to 1, the Reload counter is not active and blocks 0 to 4 can always be erased using a Write command.

4.3 EEPROM Area

The 9 blocks between addresses 7 and 15 are EEPROM blocks of 32 bits each (36 Bytes in total). (See [Figure 18](#) for a map of the area.) These blocks can be accessed using the READ_BLOCK and WRITE_BLOCK commands. The WRITE_BLOCK command for the EEPROM area always includes an Auto-Erase cycle prior to the Write cycle.

Blocks 7 to 15 can be Write-protected. Write access is controlled by the 9 bits of the OTP_Lock_Reg located at block address 255 (see [Section 4.4.1: OTP_Lock_Reg](#) for details). Once protected, these blocks (7 to 15) cannot be unprotected

Figure 18. EEPROM (Addresses 7 to 15)

Block Address	MSb b31	32-bit Block b16 b15 b14 b8 b7	LSb b0	Description
7		User Area		Lockable EEPROM
8		User Area		
9		User Area		
10		User Area		
11		User Area		
12		User Area		
13		User Area		
14		User Area		
15		User Area		

Ai12383

4.4 System Area

This area is used to modify the settings of the SRI512. It contains 4 registers: OTP_Lock_Reg, OTP_Config_Bit, Fixed Chip_ID and ST Reserved. See [Figure 19](#) for a map of this area.

A WRITE_BLOCK command in this area will not erase the previous contents. Selected bits can thus be set from 1 to 0. All bits previously at 0 remain unchanged. Once all the 32 bits of a block are at 0, the block is empty and cannot be updated any more.

Figure 19. System Area

Block Address	MSb	32-bit Block				LSb	Description
	b31	b16	b15	b14	b8	b7	
255	OTP_Lock_Reg	OTP config bit	ST Reserved	Fixed Chip_ID (Option)			OTP

ai12374

4.4.1 OTP_Lock_Reg

The 16 bits, b31 to b16, of the System Area (block address 255) are used as OTP_Lock_Reg bits in the SRI512. They control the Write access to the 16 blocks 0 to 15 as follows:

- When b16 is at 0, block 0 is Write-protected
- When b17 is at 0, block 1 is Write-protected
- When b18 is at 0, block 2 is Write-protected
- When b19 is at 0, block 3 is Write-protected
- When b20 is at 0, block 4 is Write-protected
- When b21 is at 0, block 5 is Write-protected
- When b22 is at 0, block 6 is Write-protected
- When b23 is at 0, block 7 is Write-protected
- When b24 is at 0, block 8 is Write-protected
- When b25 is at 0, block 9 is Write-protected
- When b26 is at 0, block 10 is Write-protected
- When b27 is at 0, block 11 is Write-protected
- When b28 is at 0, block 12 is Write-protected
- When b29 is at 0, block 13 is Write-protected
- When b30 is at 0, block 14 is Write-protected
- When b31 is at 0, block 15 is Write-protected.

The OTP_Lock_Reg bits cannot be erased. Once Write-protected, the blocks behave like ROM blocks and cannot be unprotected. After any modification of the OTP_Lock_Reg bits, it is necessary to send a SELECT command with a valid Chip_ID to the SRI512 in order to load the block write protection into the logic.

4.4.2 OTP_Config_Bit

Bit b15 of the System Area is used to set the behaviors of the OTP area (blocks 0 to 4). When b15 is at 1, the OTP area behaves as an EEPROM. When b15 is at 0, the OTP area behaves as OTP bits.

This bit is set by ST during production tests on customer request. It cannot be modified by the user.

4.4.3 Fixed Chip_ID (Option)

The SRI512 is provided with an anti-collision feature based on a random 8-bit Chip_ID. Prior to selecting an SRI512, an anti-collision sequence has to be run to search for the Chip_ID of the SRI512. This is a very flexible feature, however the searching loop requires time to run.

For some applications, much time could be saved by knowing the value of the SRI512 Chip_ID beforehand, so that the SRI512 can be identified and selected directly without having to run an anti-collision sequence. This is why the SRI512 was designed with an optional mask setting used to program a fixed 8-bit Chip_ID to bits b₇ to b₀ of the system area. When the fixed Chip_ID option is used, the random Chip_ID function is disabled.

5 SRI512 operation

All commands, data and CRC are transmitted to the SRI512 as 10-bit characters using ASK modulation. The start bit of the 10 bits, b_0 , is sent first. The command frame received by the SRI512 at the antenna is demodulated by the 10% ASK demodulator, and decoded by the internal logic. Prior to any operation, the SRI512 must have been selected by a SELECT command. Each frame transmitted to the SRI512 must start with a Start Of Frame, followed by one or more data characters, two CRC Bytes and the final End Of Frame. When an invalid frame is decoded by the SRI512 (wrong command or CRC error), the memory does not return any error code.

When a valid frame is received, the SRI512 may have to return data to the reader. In this case, data is returned using BPSK encoding, in the form of 10-bit characters framed by an SOF and an EOF. The transfer is ended by the SRI512 sending the 2 CRC Bytes and the EOF.

DRAFT

6 SRI512 states

The SRI512 can be switched into different states. Depending on the current state of the SRI512, its logic will only answer to specific commands. These states are mainly used during the anti-collision sequence, to identify and to access the SRI512 in a very short time. The SRI512 provides 6 different states, as described in the following paragraphs and in [Figure 20](#).

6.1 POWER-OFF State

The SRI512 is in POWER-OFF state when the electromagnetic field around the tag is not strong enough. In this state, the SRI512 does not respond to any command.

6.2 READY State

When the electromagnetic field is strong enough, the SRI512 enters the READY state. After Power-up, the Chip_ID is initialized with a random value. The whole logic is reset and remains in this state until an INITIATE() command is issued. Any other command will be ignored by the SRI512.

6.3 INVENTORY State

The SRI512 switches from the READY to the INVENTORY state after an INITIATE() command has been issued. In INVENTORY state, the SRI512 will respond to any anti-collision commands: INITIATE(), PCALL16() and SLOT_MARKER(), and then remain in the INVENTORY state. It will switch to the SELECTED state after a SELECT(Chip_ID) command is issued, if the Chip_ID in the command matches its own. If not, it will remain in INVENTORY state.

6.4 SELECTED State

In SELECTED state, the SRI512 is active and responds to all READ_BLOCK(), WRITE_BLOCK(), and GET_UID() commands. When an SRI512 has entered the SELECTED state, it no longer responds to anti-collision commands. So that the reader can access another tag, the SRI512 can be switched to the DESELECTED state by sending a SELECT(Chip_ID2) with a Chip_ID that does not match its own, or it can be placed in DEACTIVATED state by issuing a COMPLETION() command. Only one SRI512 can be in SELECTED state at a time.


6.5 DESELECTED State

Once the SRI512 is in DESELECTED state, only a SELECT(Chip_ID) command with a Chip_ID matching its own can switch it back to SELECTED state. All other commands are ignored.

6.6 DEACTIVATED State

When in this state, the SRI512 can only be turned off. All commands are ignored.

Figure 20. State Transition Diagram



7 Anti-collision

The SRI512 provides an anti-collision mechanism that searches for the Chip_ID of each device that is present in the reader field range. When known, the Chip_ID is used to select an SRI512 individually, and access its memory. The anti-collision sequence is managed by the reader through a set of commands described in [Section 5: SRI512 operation](#):

- INITIATE()
- PCALL16()
- SLOT_MARKER().


The reader is the master of the communication with one or more SRI512 device(s). It initiates the tag communication activity by issuing an INITIATE(), PCALL16() or SLOT_MARKER() command to prompt the SRI512 to answer. During the anti-collision sequence, it might happen that two or more SRI512 devices respond simultaneously, so causing a collision. The command set allows the reader to handle the sequence, to separate SRI512 transmissions into different time slots. Once the anti-collision sequence has completed, SRI512 communication is fully under the control of the reader, allowing only one SRI512 to transmit at a time.

The Anti-collision scheme is based on the definition of time slots during which the SRI512 devices are invited to answer with minimum identification data: the Chip_ID. The number of slots is fixed at 16 for the PCALL16() command. For the INITIATE() command, there is no slot and the SRI512 answers after the command is issued. SRI512 devices are allowed to answer only once during the anticollision sequence. Consequently, even if there are several SRI512 devices present in the reader field, there will probably be a slot in which only one SRI512 answers, allowing the reader to capture its Chip_ID. Using the Chip_ID, the reader can then establish a communication channel with the identified SRI512. The purpose of the anti-collision sequence is to allow the reader to select one SRI512 at a time.

The SRI512 is given an 8-bit Chip_ID value used by the reader to select only one among up to 256 tags present within its field range. The Chip_ID is initialized with a random value during the READY state, or after an INITIATE() command in the INVENTORY state.


The four least significant bits (b₀ to b₃) of the Chip_ID are also known as the CHIP_SLOT_NUMBER. This 4-bit value is used by the PCALL16() and SLOT_MARKER() commands during the anti-collision sequence in the INVENTORY state.

Figure 21. SRI512 Chip_ID Description



Each time the SRI512 receives a PCALL16() command, the CHIP_SLOT_NUMBER is given a new 4-bit random value. If the new value is 0000_b, the SRI512 returns its whole 8-bit Chip_ID in its answer to the PCALL16() command. The PCALL16() command is also used to define the slot number 0 of the anti-collision sequence. When the SRI512 receives the SLOT_MARKER(SN) command, it compares its CHIP_SLOT_NUMBER with the SLOT_NUMBER parameter (SN). If they match, the SRI512 returns its Chip_ID as a response to the command. If they do not, the SRI512 does not answer. The SLOT_MARKER(SN) command is used to define all the anti-collision slot numbers from 1 to 15.

Figure 22. Description of a Possible Anti-Collision Sequence



1. The value X in the Answer Chip_ID means a random hexadecimal character from 0 to F.

7.1 Description of an Anti-Collision Sequence

The anti-collision sequence is initiated by the INITIATE() command which triggers all the SRI512 devices that are present in the reader field range, and that are in INVENTORY state. Only SRI512 devices in INVENTORY state will respond to the PCALL16() and SLOT_MARKER(SN) anti-collision commands.

A new SRI512 introduced in the field range during the anti-collision sequence will not be taken into account as it will not respond to the PCALL16() or SLOT_MARKER(SN) command (READY state). To be considered during the anti-collision sequence, it must have received the INITIATE() command and entered the INVENTORY state.

Table 4 shows the elements of a standard anti-collision sequence. (See *Figure 23* for an example.)

Table 4. Standard Anti-Collision Sequence

Step 1	Init:	Send INITIATE(). – If no answer is detected, go to step1. – If only 1 answer is detected, select and access the SRI512. After accessing the SRI512, deselect the tag and go to step1. – If a collision (many answers) is detected, go to step2.
Step 2	Slot 0	Send PCALL16(). – If no answer or collision is detected, go to step3. – If 1 answer is detected, store the Chip_ID, Send SELECT() and go to step3.
Step 3	Slot 1	Send SLOT_MARKER(1). – If no answer or collision is detected, go to step4. – If 1 answer is detected, store the Chip_ID, Send SELECT() and go to step4.
Step 4	Slot 2	Send SLOT_MARKER(2). – If no answer or collision is detected, go to step5. – If 1 answer is detected, store the Chip_ID, Send SELECT() and go to step5.
Step N	Slop N	Send SLOT_MARKER(3 up to 14) ... – If no answer or collision is detected, go to stepN+1. – If 1 answer is detected, store the Chip_ID, Send SELECT() and go to stepN+1.
Step 17	Slot 15	Send SLOT_MARKER(15). – If no answer or collision is detected, go to step18. – If 1 answer is detected, store the Chip_ID, Send SELECT() and go to step18.
Step 18		All the slots have been generated and the Chip_ID values should be stored into the reader memory. Issue the SELECT(Chip_ID) command and access each identified SRI512 one by one. After accessing each SRI512, switch them into DESELECTED or DEACTIVATED state, depending on the application needs. – If collisions were detected between Step2 and Step17, go to Step2. – If no collision was detected between Step2 and Step17, go to Step1.

After each SLOT_MARKER() command, there may be several, one or no answers from the SRI512 devices. The reader must handle all the cases and store all the Chip_IDs, correctly decoded. At the end of the anti-collision sequence, after SLOT_MARKER(15), the reader can start working with one SRI512 by issuing a SELECT() command containing the desired Chip_ID. If a collision is detected during the anti-collision sequence, the reader has to generate a new sequence in order to identify all unidentified SRI512 devices in the field. The anti-collision sequence can stop when all SRI512 devices have been identified.

Figure 23. Example of an Anti-Collision Sequence

Command	Tag 1 Chip_ID	Tag 2 Chip_ID	Tag 3 Chip_ID	Tag 4 Chip_ID	Tag 5 Chip_ID	Tag 6 Chip_ID	Tag 7 Chip_ID	Tag 8 Chip_ID	Comments
READY State	28h	75h	40h	01h	02h	FEh	A9h	7Ch	Each tag gets a random Chip_ID
INITIATE ()	40h	13h	3Fh	4Ah	50h	48h	52h	7Ch	Each tag get a new random Chip_ID All tags answer: collisions
PCALL16()	45h	12h	30h	43h	55h	43h	53h	73h	All CHIP_SLOT_NUMBERS get a new random value Slot0: only one answer
SELECT(30h)			30h						Tag3 is identified
SLOT_MARKER(1)									Slot1: no answer
SLOT_MARKER(2)		12h							Slot2: only one answer
SELECT(12h)		12h							Tag2 is identified
SLOT_MARKER(3)				43h		43h	53h	73h	Slot3: collisions
SLOT_MARKER(4)									Slot4: no answer
SLOT_MARKER(5)	45h				55h				Slot5: collisions
SLOT_MARKER(6)									Slot6: no answer
SLOT_MARKER(N)									SlotN: no answer
SLOT_MARKER(F)									SlotF: no answer
PCALL16()	40h			41h	53h	42h	50h	74h	All CHIP_SLOT_NUMBERS get a new random value Slot0: collisions
SLOT_MARKER(1)	40h			41h			50h		Slot1: only one answer
SELECT(41h)				41h					Tag4 is identified
SLOT_MARKER(2)						42h			Slot2: only one answer
SELECT(42h)						42h			Tag6 is identified
SLOT_MARKER(3)					53h				Slot3: only one answer
SELECT(53h)					53h				Tag5 is identified
SLOT_MARKER(4)								74h	Slot4: only one answer
SELECT(74h)								74h	Tag8 is identified
SLOT_MARKER(N)									SlotN: no answer
PCALL16()	41h						50h		All CHIP_SLOT_NUMBERS get a new random value Slot0: only one answer
SELECT(50h)							50h		Tag7 is identified
SLOT_MARKER(1)	41h								Slot1: only one answer but already found for tag4
SLOT_MARKER(N)									SlotN: no answer
PCALL16()	43h								All CHIP_SLOT_NUMBERS get a new random value Slot0: only one answer
SLOT_MARKER(3)	43h								Slot3: only one answer
SELECT(43h)								43h	Tag1 is identified
									All tags are identified

ai07669

8 SRI512 commands

See the paragraphs below for a detailed description of the Commands available on the SRI512. The commands and their hexadecimal codes are summarized in [Table 5](#). A brief is given in [Appendix B](#).

Table 5. Command Code

Hexadecimal Code	Command
06h-00h	INITIATE()
06h-04h	PCALL16()
x6h	SLOT_MARKER (SN)
08h	READ_BLOCK(Addr)
09h	WRITE_BLOCK(Addr, Data)
0Bh	GET_UID()
0Ch	RESET_TO_INVENTORY
0Eh	SELECT(Chip_ID)
0Fh	COMPLETION()

8.3 SLOT_MARKER(SN) Command

Command Code = x6h

The SRI512 must be in INVENTORY state to interpret the SLOT_MARKER(SN) command.


The SLOT_MARKER Byte code is divided into two parts:

- b_3 to b_0 : 4-bit command code with fixed value 6.
- b_7 to b_4 : 4 bits known as the SLOT_NUMBER (SN). They assume a value between 1 and 15. The value 0 is reserved by the PCALL16() command.

On receiving the SLOT_MARKER() command, the SRI512 compares its CHIP_SLOT_NUMBER value with the SLOT_NUMBER value given in the command code. If they match, the SRI512 returns its Chip_ID value. If not, the SRI512 does not send any response.

The SLOT_MARKER() command, used together with the PCALL16() command, allows the reader to search for all the Chip_IDs when there are more than one SRI512 device in INVENTORY state present in the reader field range.


Figure 30. SLOT_MARKER Request Format



Request parameter:

- x: Slot number


Figure 31. SLOT_MARKER Response Format



Response parameters:

- Chip_ID of the SRI512

Figure 32. SLOT_MARKER Frame Exchange Between Reader and SRI512




8.5 COMPLETION() Command

Command Code = 0Fh

On receiving the COMPLETION() command, a SRI512 in SELECTED state switches to DEACTIVATED state and stops decoding any new commands. The SRI512 is then locked in this state until a complete reset (tag out of the field range). A new SRI512 can thus be accessed through a SELECT() command without having to remove the previous one from the field. The COMPLETION() command does not generate a response.

All SRI512 devices not in SELECTED state ignore the COMPLETION() command.

Figure 36. COMPLETION Request Format



Request parameters:

- No parameter

Figure 37. COMPLETION Response Format





Figure 38. COMPLETION Frame Exchange Between Reader and SRI512



8.6 RESET_TO_INVENTORY() Command


Command Code = 0Ch

On receiving the RESET_TO_INVENTORY() command, all SRI512 devices in SELECTED state revert to INVENTORY state. The concerned SRI512 devices are thus resubmitted to the anti-collision sequence. This command is useful when two SRI512 devices with the same 8-bit Chip_ID happen to be in SELECTED state at the same time. Forcing them to go through the anti-collision sequence again allows the reader to generate new PCALL16() commands and so, to set new random Chip_IDs.

The RESET_TO_INVENTORY() command does not generate a response.

All SRI512 devices that are not in SELECTED state ignore the RESET_TO_INVENTORY() command.

Figure 39. RESET_TO_INVENTORY Request Format



Request parameter:

- No parameter

Figure 40. RESET_TO_INVENTORY Response Format




Figure 41. RESET_TO_INVENTORY Frame Exchange Between Reader and SRI512



8.7 READ_BLOCK(Addr) Command


Command Code = 08h

On receiving the READ_BLOCK command, the SRI512 reads the desired block and returns the 4 data Bytes contained in the block. Data Bytes are transmitted with the Least Significant Byte first and each byte is transmitted with the least significant bit first.

The address byte gives access to the 16 blocks of the SRI512 (addresses 0 to 15). READ_BLOCK commands issued with a block address above 15 will not be interpreted and the SRI512 will not return any response, except for the System area located at address 255.

The SRI512 must have received a SELECT() command and be switched to SELECTED state before any READ_BLOCK() command can be accepted. All READ_BLOCK() commands sent to the SRI512 before a SELECT() command is issued are ignored.


Figure 42. READ_BLOCK Request Format



Request parameter:

- ADDRESS: block addresses from 0 to 15, or 255


Figure 43. READ_BLOCK Response Format



Response parameters:

- DATA 1: Less significant data Byte
- DATA 2: Data Byte
- DATA 3: Data Byte
- DATA 4: Most significant data Byte

Figure 44. READ_BLOCK Frame Exchange Between Reader and SRI512



8.8 WRITE_BLOCK (Addr, Data) Command

Command Code = 09h

On receiving the WRITE_BLOCK command, the SRI512 writes the 4 bytes contained in the command to the addressed block, provided that the block is available and not Write-protected. Data Bytes are transmitted with the Least Significant Byte first, and each byte is transmitted with the least significant bit first.

The address Byte gives access to the 16 blocks of the SRI512 (addresses 0 to 15). WRITE_BLOCK commands issued with a block address above 15 will not be interpreted and the SRI512 will not return any response, except for the System area located at address 255.

The result of the WRITE_BLOCK command is submitted to the addressed block. See the following paragraphs for a complete description of the WRITE_BLOCK command:

- [Figure 12: Resettable OTP Area \(addresses 0 to 4\) when OTP_Config bit = 0.](#)
- [Figure 16: Binary Counter \(addresses 5 to 6\).](#)
- [Figure 18: EEPROM \(Addresses 7 to 15\).](#)

The WRITE_BLOCK command does not give rise to a response from the SRI512. The reader must check after the programming time, t_{W} , that the data was correctly programmed. The SRI512 must have received a SELECT() command and be switched to SELECTED state before any WRITE_BLOCK command can be accepted. All WRITE_BLOCK commands sent to the SRI512 before a SELECT() command is issued, are ignored.

Figure 45. WRITE_BLOCK Request Format

SOF	WRITE_BLOCK	ADDRESS	DATA 1	DATA 2	DATA 3	DATA 4	CRC _L	CRC _H	EOF
	09h	8 blts	8 blts	8 blts	8 blts	8 blts	8 blts	8 blts	

AI07687

Request parameters:

- ADDRESS: block addresses from 0 to 15, or 255
- DATA 1: Less significant data Byte
- DATA 2: Data Byte
- DATA 3: Data Byte
- DATA 4: Most significant data Byte.

Figure 46. WRITE_BLOCK Response Format





Figure 47. WRITE_BLOCK Frame Exchange Between Reader and SRI512




8.9 GET_UID() Command

Command Code = 0Bh

On receiving the GET_UID command, the SRI512 returns its 8 UID Bytes. UID Bytes are transmitted with the Least Significant Byte first, and each byte is transmitted with the least significant bit first.

The SRI512 must have received a SELECT() command and be switched to SELECTED state before any GET_UID() command can be accepted. All GET_UID() commands sent to the SRI512 before a SELECT() command is issued, are ignored.


Figure 48. GET_UID Request Format



Request parameter:

- No parameter

Figure 49. GET_UID Response Format



Response parameters:

- UID 0: Less significant UID Byte
- UID 1 to UID 6: UID Bytes
- UID 7: Most significant UID Byte.

Unique Identifier (UID)

Members of the SRI512 family are uniquely identified by a 64-bit Unique Identifier (UID). This is used for addressing each SRI512 device uniquely after the anti-collision loop. The UID complies with ISO/IEC 15963 and ISO/IEC 7816-6. It is a read-only code, and comprises (as summarized in *Figure 50*):

- an 8-bit prefix, with the most significant bits set to D0h
- an 8-bit IC Manufacturer code (ISO/IEC 7816-6/AM1) set to 02h (for STMicroelectronics)
- a 6-bit IC code set to 00 0110b = 6d for SRI512
- a 42-bit Unique Serial Number

Figure 50. 64-bit Unique Identifier of the SRI512





Figure 51. GET_UID Frame Exchange Between Reader and SRI512



8.10 Power-On State

After Power-On, the SRI512 is in the following state:

- It is in the low-power state.
- It is in READY state.
- It shows highest impedance with respect to the reader antenna field.
- It will not respond to any command except INITIATE().

9 Maximum rating

Stressing the device above the rating listed in the Absolute Maximum Ratings table may cause permanent damage to the device. These are stress ratings only and operation of the device at these or any other conditions above those indicated in the Operating sections of this specification is not implied. Exposure to Absolute Maximum Rating conditions for extended periods may affect device reliability. Refer also to the STMicroelectronics SURE Program and other relevant quality documents.

Table 6. Absolute Maximum Ratings

Symbol	Parameter	Min.	Max.	Unit	
T_{STG} , h_{STG} , t_{STG}	Storage Conditions	Wafer	15	25	°C
				23	months
			kept in its antistatic bag		
		A3, A4, A5	15	25	°C
			40%	60%	RH
				2	years
I_{CC}	Supply Current on AC0 / AC1	-20	20	mA	
V_{MAX}	Input Voltage on AC0 / AC1	-7	7	V	
V_{ESD}	Electrostatic Discharge Voltage	Machine Model ⁽¹⁾	-100	100	V
		Human Body Model ⁽¹⁾	-1000	1000	V
		Human Body Model ⁽²⁾	-4000	4000	V

1. Mil. Std. 883 - Method 3015

2. ESD test: ISO10373-6 for proximity cards

10 DC and AC parameters

Table 7. Operating Conditions

Symbol	Parameter	Min.	Max.	Unit
T_A	Ambient Operating Temperature	-20	85	°C

Table 8. DC Characteristics


Symbol	Parameter	Condition	Min	Max	Unit
V_{CC}	Regulated Voltage		2.5	3.5	V
I_{CC}	Supply Current (Active in Read)	$V_{CC} = 3.0V$		100	μA
I_{CC}	Supply Current (Active in Write)	$V_{CC} = 3.0V$		250	μA

Table 9. AC Characteristics⁽¹⁾

Symbol	Parameter	Condition	Min	Max	Unit
f_{CC}	External RF Signal Frequency		13.553	13.567	MHz
$MI_{CARRIER}$	Carrier Modulation Index	$MI=(A-B)/(A+B)$	8	14	%
t_{RFR}, t_{RFF}	10% Rise and Fall times		0.8	2.5	μs
t_{RFSBL}	Minimum Pulse Width for Start bit	$ETU = 128/f_{CC}$	9.44		μs
t_{JIT}	ASK modulation Data Jitter	Coupler to SRI512	-2	+2	μs
$t_{MIN CD}$	Minimum Time from Carrier Generation to First Data		5		ms
f_S	Subcarrier Frequency	$f_{CC}/16$	847.5		kHz
t_0	Antenna Reversal Delay	$128/f_S$	151		μs
t_1	Synchronization Delay	$128/f_S$	151		μs
t_2	Answer to New Request Delay	14 ETU	132		μs
t_{DR}	Time Between Request Characters	Coupler to SRI512	0	57	μs
t_{DA}	Time Between Answer Characters	SRI512 to Coupler	0		μs
t_W	Programming Time for WRITE	With no Auto-Erase Cycle (OTP)		3	ms
		With Auto-Erase Cycle (EEPROM)		5	ms
		Binary Counter Decrement		7	ms

1. All timing measurements were performed on a reference antenna with the following characteristics:
 External size: 75mm x 48mm
 Number of turns: 3
 Width of conductor: 1mm
 Space between 2 conductors: 0.4mm
 Value of the coil: 1.4 μ H
 Tuning Frequency: 14.4MHz.

Figure 52. SRI512 Synchronous Timing, Transmit and Receive



11 Package mechanical

Figure 53. A3 Antenna Specification




Table 10. A3 Antenna Specification

Symbol	Parameter	Type	Min	Max	Unit
A	Coil Width	38	37.5	38.5	mm
B	Coil Length	38	37.5	38.5	mm
A1	Inlay Width	43	42.5	43.5	mm
B1	Inlay Length	43	42.5	43.5	mm
	Overall Thickness of Copper Antenna Coil	110	90	130	μm
	Silicon Thickness	180	165	195	μm
Q	Unloaded Q Value	40			
F_{NOM}	Unloaded Free-air Resonance	15.1			MHz
P_A	H-field Energy for Device Operation		0.5 114		A/m db μ A/m

Figure 54. A4 Antenna Specification




Table 11. A4 Antenna Specification

Symbol	Parameter	Type	Min	Max	Unit
A	Coil Width	15	14.5	15.5	mm
B	Coil Length	15	14.5	15.5	mm
A1	Inlay Width	19	18.5	19.5	mm
B1	Inlay Length	19	18.5	19.5	mm
	Overall Thickness of Copper Antenna Coil	110	90	130	μm
	Silicon Thickness	180	165	195	μm
Q	Unloaded Q Value	30			
F _{NOM}	Unloaded Free-air Resonance	14.5			MHz
P _A	H-field Energy for Device Operation		1.5 123.5		A/m dbμA/m

Figure 55. A5 Antenna Specification




Table 12. A5 Antenna Specification

Symbol	Parameter	Type	Min	Max	Unit
A	Coil Width	42	41.5	42.5	mm
B	Coil Length	65	64.5	65.5	mm
A1	Inlay Width	46	45.5	46.5	mm
B1	Inlay Length	70	69.5	70.5	mm
	Overall Thickness of Copper Antenna Coil	140	130	150	μm
	Silicon Thickness	180	165	195	μm
Q	Unloaded Q Value	30			
F_{NOM}	Unloaded Free-air Resonance	14.8			MHz
P_A	H-field Energy for Device Operation		0.25 108		A/m dB $\mu\text{A/m}$

12 Part numbering

Table 13. Ordering Information Scheme

Example:	SRI512	-	W4 / XXX
Device Type	SRI512		
Package	W4 = 180 μm ± 15 μm UnsaWn Wafer SBN18 = 180μm ± 15 μm Bumped and Sawn Wafer on 8-inch Frame A3T = 38mm x 38mm Copper Antenna on Continuous Tape A3S = 38mm x 38mm Copper Singulated Adhesive Antenna on Tape A4T = 15mm x 15mm Copper Antenna on Continuous Tape A4S = 15mm x 15mm Copper Singulated Adhesive Antenna on Tape A5T = 42mm x 65mm Copper Antenna on Continuous Tape A5S = 42mm x 65mm Copper Singulated Adhesive Antenna on Tape		
Customer Code	XXX = Given by STMicroelectronics		

Note: *Devices are shipped from the factory with the memory content bits erased to 1.*
 For a list of available options (Speed, Package, etc.) or for further information on any aspect of this device, please contact your nearest ST Sales Office.

Appendix A ISO14443 type B CRC calculation

```
#include <stdio.h>
#include <stdlib.h>
#include <string.h>
#include <ctype.h>
#define BYTE unsigned char
#define USHORT unsigned short

unsigned short UpdateCrc(BYTE ch, USHORT *lpwCrc)
{
    ch = (ch^(BYTE)((*lpwCrc) & 0x00FF));
    ch = (ch^(ch<<4));
    *lpwCrc = (*lpwCrc >> 8)^((USHORT)ch <<
8)^((USHORT)ch<<3)^((USHORT)ch>>4);
    return(*lpwCrc);
}

void ComputeCrc(char *Data, int Length, BYTE *TransmitFirst, BYTE
*TransmitSecond)
{
    BYTE chBlock; USHORTt wCrc;
    wCrc = 0xFFFF; // ISO 3309
    do
    {
        {
            chBlock = *Data++;
            UpdateCrc(chBlock, &wCrc);
        } while (--Length);
    }
    wCrc = ~wCrc; // ISO 3309
    *TransmitFirst = (BYTE) (wCrc & 0xFF);
    *TransmitSecond = (BYTE) ((wCrc >> 8) & 0xFF);
    return;
}

int main(void)
{
    BYTE BuffCRC_B[10] = {0x0A, 0x12, 0x34, 0x56}, First, Second, i;
    printf("Crc-16 G(x) = x^16 + x^12 + x^5 + 1");
    printf("CRC_B of [ ");
    for(i=0; i<4; i++)
        printf("%02X ",BuffCRC_B[i]);
    ComputeCrc(BuffCRC_B, 4, &First, &Second);
    printf("] Transmitted: %02X then %02X.", First, Second);
    return(0);
}
```

Appendix B SRI512 command brief

Figure 56. INITIATE Frame Exchange Between Reader and SRI512




Figure 57. PCALL16 Frame Exchange Between Reader and SRI512




Figure 58. SLOT_MARKER Frame Exchange Between Reader and SRI512




Figure 59. SELECT Frame Exchange Between Reader and SRI512




Figure 60. COMPLETION Frame Exchange Between Reader and SRI512




Figure 61. RESET_TO_INVENTORY Frame Exchange Between Reader and SRI512



Figure 62. READ_BLOCK Frame Exchange Between Reader and SRI512




Figure 63. WRITE_BLOCK Frame Exchange Between Reader and SRI512





Figure 64. GET_UID Frame Exchange Between Reader and SRI512



13 Revision history

Table 14. Document revision history

Date	Revision	Changes
06-Mar-2006	1	Initial release.

DRAFT

Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED REPRESENTATIVE OF ST, ST PRODUCTS ARE NOT DESIGNED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS, WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2006 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com